FU8230

Secvest 2WAY Wireless Indoor Sounder

The Secvest wireless indoor sounder is an optional accessory for the Secvest 2WAY. As a purely acoustic signalling unit, it supports the wireless outdoor siren and the alarm panel of the Secvest 2WAY with a 90 dB tone. The sounder and the alarm panel communicate on 868.6625 MHz, a radio frequency that has been specially reserved for security purposes. The wireless indoor sounder can be powered via a batteries or power supply. When using batteries, the service life is approx. 2 years. A weakening battery is indicated at the alarm panel of the Secvest 2WAY and a red LED on the sounder.

Product highlights:

- For acoustic support of the Secvest and the wireless outside siren
- Robust injection molded ABS housing
- Loud signalling unit
- DC power supply for use without batteries (optional)
-

© 2012 ABUS Security–Center GmbH & Co. KG, Errors and omissions excepted.

FU8230

Secvest 2WAY Wireless Indoor Sounder

Technical Data	
Duplex antenna technology	868.6625 MHz
Battery service life	More than 2 years
Acoustic pressure	90 dB(A) @ 1 m
Simplex function for multi–siren systems	Optional
DC network connection for operating without a battery	yes
LED indication for weak battery and teaching–in in UVM	yes
Dimensions (WxHxD)	122x208x60 mm

© 2012 ABUS Security–Center GmbH & Co. KG, Errors and omissions excepted.